



#23326

Источник бесперебойного питания (ИБП), 800 ВА

Надежный ИБП мощностью 800 ВА с резервным питанием от батареи и с 6 розетками. Идеально подходит для питания и защиты ваших электронных устройств

Key features

- Надежный ИБП мощностью 800 ВА со встроенным аккумулятором
- Обеспечивает временную подачу электричества во время отключения энергии; предотвращает потерю данных и повреждение оборудования
- 3 аккумулятора и 3 настенные розетки с защитой от перенапряжения для подключения компьютера, периферийных устройств, сетевого оборудования, телевизора с плоским экраном, автоматизированных систем для дома или аварийной сигнализации
- Разъемы с защитой от выбросов напряжения для предотвращения повреждений от скачков, падений и колебаний напряжения
- Функция автоматической регулировки напряжения обеспечивает стабильное выходное напряжение 230 В
- Понятное визуальное и звуковое оповещение



What's in the box

- Блок ИБП
- Кабель питания
- Руководство пользователя
- Крепления и болты

System requirements

- Подключение к заземленной настенной розетке

800^{VA}

Battery



Surge
Protected



3x Battery
Protected



6x Power
outlets



Back-up power

The Maxxon uninterruptible power supply (UPS) with built-in 800VA battery can keep electronic devices up and running temporarily if the main power goes down. Connecting your hardware to one of the three battery-powered outlets offers valuable time to save your work or in-game progress and safely shut down the equipment after a power outage.

Protect your equipment

All power outlets are surge-protected and the Automatic Voltage Regulation (AVR) function automatically corrects too high or too low voltage to ensure a stable 230V output voltage. The Maxxon UPS also protects your hardware from damage by surges, spikes and fluctuations from the power grid.



Multi-purpose

The Maxxon UPS is easily set up and can be used with electronic devices up to 360W, such as your PC, home automation system, alarm, NAS server, router/modem or gaming console. The convenient top-mounted outlets make sure you can place the Maxxon anywhere: on the floor, on your desk or even mounted to the wall.

Clear alerts

The UPS is equipped with clear optical and audible indicators to alert you when necessary. In this way, you can act immediately during a power outage and save your hard work before shutting down the device. Both your hardware and data are safe from damage when using the Maxxon UPS!



GENERAL

Height of main product (in mm)	93 mm	Width of main product (in mm)	202 mm
Depth of main product (in mm)	293 mm	Total weight	4550 g
Weight of main unit	4400 g		

PROTECTION

Protections	Child safety shutter, over-charge, over-discharge, over-load	Auto Voltage Regulation	True
RFI-filter	False	Surge protected AC outlets	True
Surge protected phone line	False		

OUTPUT

Waveform type	Simulated sine wave	Frequency response UPS	50Hz +/- 1Hz
Output voltage range	Nominal voltage +/- 10%		

POWER

Number of batteries	1	Battery composition (Alkaline, Li-ion, etc.)	Lead Acid
Battery capacity (Ah)	7 Ah	Battery capacity (V)	12 V

FEATURES

Management function (USB)	False	Audible alarm	True
Software included	False		

INPUT

Nominal input voltage	220-240Vac	Operating voltage range	162-290Vac
------------------------------	------------	--------------------------------	------------

CONNECTIVITY

Cables included	Yes Power cable
------------------------	-----------------

CONTROL

Indicators	Battery, Overload, Power on/off
-------------------	---------------------------------



PRODUCT VISUAL 1



PRODUCT PICTORIAL 1



PRODUCT PICTORIAL 2



PRODUCT PICTORIAL 3



PRODUCT PICTORIAL 4




PRODUCT PICTORIAL 5



PRODUCT ESHOT 1



PRODUCT TOP 1



PRODUCT BOTTOM 1



PACKAGE VISUAL 1



PACKAGE FRONT 1



LIFESTYLE VISUAL 1